



DC-DC Switching Regulator and Controller Selector Guide

Step-Down Buck Switching Regulator - Internal Switch

Device	Vin (V)		Vout Options (Adj Range)	Iout	Fsw (kHz)	Mode	Enable	Soft-Start	Comments	Temp Range (°C)	Package
	Min	Max									
NCP3101	4.5	13.2	Down to 0.8 V	6.0 A	275	Voltage	✓	✓	Highly integrated 6 A output	-40 to 85	QFN-40
NCP3102	4.5	13.2	Down to 0.8 V	10.0 A	275	Voltage	✓	✓	Highly integrated 10 A output	-40 to 85	QFN-40
NCP3120/2	4.5	13.2	Down to 0.8 V	2.0/2.0 A	200-750/ 200-2200	Voltage	✓	✓	Auto tracking and sequencing; 180° Out-of-phase operation	-40 to 85	QFN-32
NCP3121/3	4.5	13.2	Down to 0.8 V	3.0/3.0 A	200-750/ 200-2200	Voltage	✓	✓	Auto tracking and sequencing; 180° Out-of-phase operation	-40 to 85	QFN-32
CS51411/3	4.5	40	Down to 1.276 V	1.5 A	260/520	Voltage	✓	✓	Sync capability; Pin-Compatible with LT1375 and LT1376	-40 to 85	SOIC-8, DFN-8
CS51412/4	4.5	40	Down to 1.276 V	1.5 A	260/520	Voltage	✓	✓	External Bias; Pin-Compatible with LT1375 and LT1376	-40 to 85	SOIC-8, DFN-8
NCV51411	4.5	40	Down to 1.276 V	1.5 A	260	Voltage	✓	✓	Automotive version	-40 to 125	SOIC-8, DFN-8
LM2574	4.75	40	3.3, 5, 12, 15, Adj (1.23 to 37 V)	0.5 A	52	Voltage	✓		No external compensation required	-40 to 125	D2PAK, TO-220
LM2575	4.75	40	3.3, 5, 12, 15, Adj (1.23 to 37 V)	1.0 A	52	Voltage	✓		No external compensation required	-40 to 125	D2PAK, TO-220
LM2576	4.75	40	3.3, 5, 12, 15, Adj (1.23 to 37 V)	3.0 A	52	Voltage	✓		No external compensation required	-40 to 125	D2PAK, TO-220
NCP1595A	4.0	5.5	Down to 0.8 V	1.5 A	1200	Current	✓	✓	Internal compensation; Synchronous Rectification	0 to 85	DFN-6
MC34166	7.5	40	Down to 5.0 V	3.0 A	72	Voltage			Cycle-by-Cycle current limit	0 to 70	D2PAK, TO-220
MC33166	7.5	40	Down to 5.0 V	3.0 A	72	Voltage			Internal thermal shutdown	-40 to 85	D2PAK, TO-220
MC33167	7.0	40	Down to 5.0 V	5.0 A	72	Voltage			Large 5.0 A output capability	-40 to 85	D2PAK, TO-220
MC34167	7.0	40	Down to 5.0 V	5.0 A	72	Voltage			Standby Mode < 36 µA	0 to 70	D2PAK, TO-220
NCP1500	2.7	5.4	1.0, 1.3, 1.5, 1.8 V	300 mA	270 - 630	Current			PWM or Linear mode. Can be programmed to work in Linear LDO Regulator mode. External Sync.	-40 to 85	Micro8™
NCP1501	2.7	5.2	1.05, 1.35, 1.57, 1.8 V	300 mA	500-1000	Current			Synchronous Rectification. Can be programmed to work in Linear LDO Regulator mode. External Sync.	-40 to 85	Micro8™
NCP1526	2.7	5.5	PWM - 1.2V; LDO - 2.8 V Other options available	PWM: 400 mA LDO: 150 mA	3000	Voltage	✓	✓	Dual output: PWM + LDO. Synchronous Rectification	-40 to 85	Thin DFN-10
NCP1510	2.5	5.2	1.05, 1.35, 1.57, 1.8 V	300 mA	450-1000	Current	✓	✓	Synchronous Rectification. Can be programmed to work in Low Iq (14 uA) Pulsed mode at light loads. External Sync.	-40 to 85	MicroBump-9
NCP1530	2.7	5	2.5, 2.7, 3.0, 3.3 V	600 mA	600 - 1200	Current	✓	✓	Automatic PWM/PFM mode. External Synchronization Up to 1.2 MHz	-40 to 85	Micro8™
NCP1521B	2.7	5.5	0.9 - 3.9 V	600 mA	1500	Current	✓	✓	Auto PWM/PFM mode. Synchronous Rectification	-40 to 85	Thin SOT-23-5, Thin DFN-6
NCP1522B	2.7	5.5	0.9 - 3.3 V	600 mA	3000	Voltage	✓	✓	Auto PWM/PFM mode. Synchronous Rectification	-40 to 85	Thin SOT-23-5, Thin DFN-6
NCP1523B	2.7	5.5	0.9 - 3.3 V	600 mA	3000	Voltage	✓	✓	PWM mode. Synchronous Rectification	-40 to 85	MicroBump-8
NCP1529	2.7	5.5	1.2, 1.8, Adj (0.9-3.3 V)	1.0 A	1700	Current	✓	✓	Auto PWM/PFM mode. Synchronous Rectification	-40 to 85	Thin SOT-23-5

Step-Up Boost Switching Regulator - Internal Switch

Device	Vin (V)		Vout Options (Adj Range)	Iout	Fsw (kHz)	Mode	Enable	Soft-Start	Comments	Temp Range (°C)	Package
	Min	Max									
NCP1403	1.2	5.5	Up to 15 V	50 mA	300	Current	✓	✓	PFM mode	-40 to 85	SOT-23-5
NCP1406	1.4	5.5	Up to 25 V	50 mA	1000	Current	✓	✓	PFM mode	-40 to 85	SOT-23-5
NCP1400	0.8	5.5	1.9 - 5.0 V	100 mA	180	Voltage	✓	✓	PWM mode	-40 to 85	SOT-23-5
NCP1402	0.8	5.5	1.8 - 5.0 V	200 mA	180	Voltage	✓	✓	PFM mode	-40 to 85	SOT-23-5
NCP1410	1.0	5.5	Vin to 5.5 V	250 mA	600	Current	✓		PFM mode. Synchronous Rectification, Low-battery detect	-40 to 85	Micro8™
NCP1423	0.8	Vout	1.8 - 5.5 V	400 mA	600	Current	✓	✓	PFM mode. Synchronous Rectification, True-cutoff, Low-battery detect	-40 to 85	Micro-10
NCP1421	1.0	5.0	1.5 - 5.0 V	600 mA	1200	Current	✓	✓	PFM Sync-rect, True-cutoff, Low-battery detect	-40 to 85	Micro8
NCP1422	1.0	5.0	1.5 - 5.0 V	800 mA	1200	Current	✓	✓	PFM mode. Synchronous Rectification, True-cutoff, Low-battery detect	-40 to 85	DFN-10
NCP5030	2.7	5.5	2.2 - 5.5 V	1.2 A	1000	Current	✓	✓	Buck/ Boost Converter - can supply either regulated current or regulated output voltage	-40 to 85	DFN-12
CS5171	2.7	30	1.276 to 40 V	1.5 A	280	Current		✓	LT1372/1373 Compatible	-40 to 85	SOIC-8
CS5172	2.7	30	-2.5 to 40 V	1.5 A	280	Current		✓	Flyback & SEPIC	-40 to 85	SOIC-8
CS5173	2.7	30	1.276 to 40 V	1.5 A	560	Current		✓	Easy External Synchronization	-40 to 85	SOIC-8
CS5174	2.7	30	-2.5 to 40 V	1.5 A	560	Current		✓	Negative feedback polarity	-40 to 85	SOIC-8

Multi-Topology (Step-Up, Step-Down, Inverting) Switching Regulator - Internal Switch

Device	Vin (V)		Vout Options (Adj Range)	Iout (A)	Fsw (kHz)	Enable	Mode	Step Up	Step Down	Step Up/Down	Inv	Comments	Temp Range (°C)	Package
	Min	Max												
MC34063	3.0	40	Down to 2.5 V	1.5	Up to 100	✓	Hysteretic	✓	✓	✓	✓	Simple & Flexible regulator	0 to 70	SOIC-8, PDIP-8
MC33063	3.0	40	Down to 2.5 V	1.5	Up to 100	✓	Hysteretic	✓	✓	✓	✓	Minimal number of external components	-40 to 85	SOIC-8, PDIP-8
NCV33063	3.0	40	Down to 2.5 V	1.5	Up to 100	✓	Hysteretic	✓	✓	✓	✓	Automotive version	-40 to 125	SOIC-8
NCP3063	3.0	40	Down to 2.5 V	1.5	Up to 250	✓	Hysteretic	✓	✓	✓	✓	Higher Fsw for optimized size & efficiency	-40 to 85	PDIP-8, SOIC-8, DFN-8
NCP3065	3.0	40	Down to 0.2 V	1.5	Up to 250	✓	Hysteretic	✓	✓	✓	✓	Driver for HB-LED/constant current source	-40 to 85	DFN-8, SOIC-8, PDIP-8
CS5171	2.7	30	1.276 to 40 V	1.5	280		Current	✓			✓	LT1372/1373 Compatible	-40 to 85	SOIC-8
CS5172	2.7	30	-2.5 to 40 V	1.5	280		Current	✓			✓	Flyback & SEPIC	-40 to 85	SOIC-8
CS5173	2.7	30	1.276 to 40 V	1.5	560		Current	✓			✓	Easy External Synchronization	-40 to 85	SOIC-8
CS5174	2.7	30	-2.5 to 40 V	1.5	560		Current	✓			✓	Negative feedback polarity	-40 to 85	SOIC-8
MC34166	7.5	40	Down to 5.0 V	3.0	72		Voltage		✓	✓	✓	Cycle-by-Cycle current limit	0 to 70	D2PAK, TO-220
MC33166	7.5	40	Down to 5.0 V	3.0	72		Voltage		✓	✓	✓	Internal thermal shutdown	-40 to 85	D2PAK, TO-220
MC34163	2.5	40	Down to 1.25 V	3.4	Up to 100	✓	Hysteretic	✓	✓	✓	✓	Simple & Flexible regulator	0 to 70	SOIC-16W, PDIP-16
MC33163	2.5	40	Down to 1.25 V	3.4	Up to 100	✓	Hysteretic	✓	✓	✓	✓	Minimal number of external components	-40 to 85	SOIC-16W, PDIP-16
NCP3163	2.5	40	Down to 1.25 V	3.4	Up to 300	✓	Hysteretic	✓	✓	✓	✓	Higher Fsw for optimized size & efficiency	-40 to 85	SOIC-16WEP
MC34167	7.0	40	Down to 5.0 V	5.0	72		Voltage		✓	✓	✓	Large 5.0A output capability	0 to 70	D2PAK, TO-220
MC33167	7.0	40	Down to 5.0 V	5.0	72		Voltage		✓	✓	✓	Standby Mode < 36 µA	-40 to 85	D2PAK, TO-220

Switching Controllers for Step-Down Non-Isolated Topologies

Device	Vin (V)		Vout Options (Adj Range)	Vout Accuracy	Fsw (kHz)	Mode	Enable	Soft- Start	Sync	Comments	Temp Range (°C)	Package
	Min	Max										
NCP5211	4.5	14	Down to 1.0 V	1.5%	150 - 750	Voltage	✓	✓	✓	1.5 A drive capability	0 to 70	SOIC-14
NCP5211B	4.5	14	Down to 1.0 V	1.5%	150 - 750	Voltage	✓	✓	✓	1.5 A drive capability	-40 to 85	SOIC-14
CS51031	4.5	16	Down to 1.25 V	2%	200 - 700	Hysteretic		✓		No compensation required; PFET	-40 to 85	SOIC-8
CS51033	3.3	5.0	Down to 1.25 V	2%	200 - 700	Hysteretic		✓		No compensation required; PFET	-40 to 85	SOIC-8
SG3525	8.0	35	Down to 5.1 V	1%	100 - 400	Voltage	✓	✓		Flexible configurations; ST Compatible	0 to 70	SOIC-16W, PDIP-16
NCP1580	4.5	15	Down to 0.8 V	1.5%	350	Voltage		✓	✓	1.5 A gate drive; 90% duty cycle	-40 to 85	SOIC-8
NCP1582/A	4.5	15	Down to 0.8 V	1.5%	350	Voltage	✓	✓	✓	0.7 A gate drive; Short Circuit Protection	-40 to 85	SOIC-8
NCP1583	4.5	15	Down to 0.8 V	1.5%	300	Voltage	✓	✓	✓	0.7 A gate drive; Short Circuit Protection	-40 to 85	SOIC-8
NCP1571	2.0	12	Down to 0.980 V	1.0%	200	Voltage	✓	✓	✓	12 V bias supply	0 to 125	SOIC-8
NCP1575	2.0	12	Down to 0.980 V	1.0%	200 - 500	Voltage		✓	✓	12 V bias supply	0 to 125	SOIC-8
NCP1550	2.5	5.5	1.8 - 3.3 V (factory prefixed)	2.0%	600	Voltage	✓	✓		Auto PWM/ PFM mode; 2 A drive capability	-40 to 85	SOT-23-5

Dual Switching Controllers for Step-Down Non-Isolated Topologies

Device	Vin (V)		Vout Options (Adj Range)	Vout Accuracy	Fsw (kHz)	Mode	Enable	Soft- Start	Sync	Comments	Temp Range (°C)	Package
	Min	Max										
NCP5422	10.8	13.2	Down to 1.0 V	2.0%	150 - 600	Voltage	✓	✓	✓	Hiccup mode overcurrent protection	0 to 70	SOIC-16
NCP5423	10.8	13.2	Down to 1.0 V	1.0%	150 - 600	Voltage	✓	✓	✓	1% Voltage reference	0 to 70	SOIC-16
NCP5424	10.8	13.2	Down to 1.0 V	2.0%	150 - 600	Voltage	✓	✓	✓	Hiccup & cycle-by-cycle overcurrent	0 to 70	SOIC-16
NCP5425	4.6	13.2	Down to 0.8 V	1.0%	150 - 750	Voltage	✓	✓	✓	1.5A peak drive capability	0 to 125	TSSOP-20
TL494	7.0	40	0.3 V Ext Adj	5.0%	Up to 200	Voltage				Buck, boost, forward, flyback	-40 to 125	SOIC-16, PDIP-16
TL594	7.0	40	0.3 V Ext Adj	1.5%	Up to 300	Voltage				Buck, boost, forward, flyback	-40 to 85	SOIC-16, PDIP-16, TSSOP-16

Switching Controllers for Step-Up Non-Isolated Topologies

Device	Vin (V)		Vout Options (Adj Range)	Vout Accuracy	Fsw (kHz)	Mode	Enable	Soft- Start	Sync	Comments	Temp Range (°C)	Package
	Min	Max										
NCP1450	0.9	5.5	1.9 - 5.0 V (factory prefixed)	2.5%	180	Voltage	✓	✓		PWM mode	-40 to 85	SOT-23-5

Switching Controllers for Step-Down Isolated Topologies

Device	Vin (V)		Vout Options (Adj Range)	Vout Accuracy	Fsw (kHz)	Mode	Enable	Soft- Start	Sync	Comments	Temp Range (°C)	Package
	Min	Max										
CS5124	7.7	75	External	-	400	Current	✓	✓		Small PCB footprint; Bias for startup	-40 to 105	SOIC-8
CS51221	3.3	72	Down to 1.26V	2%	Up to 1000	Voltage		✓		Programmable features; Bias for startup	-40 to 85	SOIC-16, TSSOP-16
CS51021	3.3	72	Down to 5.0V	1%	200 - 1000	Current		✓		Sync; Bias for startup	-40 to 85	SOIC-16, TSSOP-16
CS51022	3.3	72	Down to 5.0V	1%	200 - 1000	Current		✓		Sleep mode; Bias for startup	-40 to 85	SOIC-16, TSSOP-16
NCP1030	10	200	2.5 Up to Vin	2%	Up to 1000	Voltage	✓	✓		PoE applications; Integrated Switch	-40 to 125	Micro8™
NCP1031	10	200	2.5 Up to Vin	2%	Up to 1000	Voltage	✓	✓		PoE applications; Integrated Switch	-40 to 125	SOIC-8

Sales and Design Assistance from ON Semiconductor



www.onsemi.com

NORTH AMERICA SALES OFFICES & REP FIRMS

Alabama	Huntsville	e-Components	(256) 533-2444
	Huntsville	ON Sales Office	(256) 774-1004
Arizona	Phoenix	Centaur Corporation	(480) 839-2320
California	Irvine	Centaur Corporation	(949) 261-2123
	Los Angeles	Centaur Corporation	(805) 579-0519
	San Diego	Centaur Corporation	(858) 278-4950
CANADA	All Regions	Astec	(905) 607-1444
Colorado	Englewood	ON Sales Office	Karl Hill: (720) 895-1367 Mike Barone: (303) 670-8000
Connecticut	Monroe	Impact Technical Sales	(203) 268-7229
Florida	Boca Raton	e-Components	(561) 289-1379
	Lake Mary	e-Components	(407) 804-0042
	Plantation	ON Sales Office	(954) 325-1223
	Palm Harbor	e-Components	(727) 937-3016
	Melbourne	e-Components	(321) 676-5659
Georgia	Duluth	e-Components	(678) 380-5080
Illinois	Hoffman Estates	Stan Clothier	(847) 781-4010
Indiana	Fishers	Bear VAI	(317) 570-0707
	Kokomo	ON Sales Office	(765) 865-2091
Iowa	Cedar Rapids	Stan Clothier	(319) 393-1576
Kansas	Overland Park	Stan Clothier	(913) 894-1675
Maryland	Columbia	Third Wave Solutions	(410) 290-5990
Massachusetts	Burlington	Impact Technical Sales	(781) 238-8888
	Lowell	ON Sales Office	(978) 452-6075
Michigan	Livonia	ON Sales Office	(734) 953-6848
Minnesota	Eden Prairie	Stan Clothier	(952) 944-3456
Missouri	St. Charles	Stan Clothier	(636) 916-3777
New Jersey	Denville	CJR Associates	(973) 625-2796
New York	Long Island	CJR Associates	(973) 625-2796
	New York City	CJR Associates	(973) 625-2796
	Rochester	TriTech	(716) 385-6500
	Binghamton	TriTech	(607) 722-3580
Ohio	Brecksville	Bear VAI	(937) 748-1341
Oregon	Portland	SiFore Technical Sales	(503) 977-6267
Pennsylvania	Hatboro	Delta Technical Sales	(215) 957-0600
Texas	Austin	West Associates	(512) 343-1199
	Richardson	West Associates	(972) 680-2800
Washington	Bellevue	SiFore Technical Sales	(425) 990-4701
Wisconsin	Statewide	Stan Clothier	(847) 781-4010

ON Semiconductor Distribution Partners

Arrow Electronics	www.arrow.com	(800) 777-2776
Avnet	www.em.avnet.com	(800) 332-8638
Chip Supply	www.chipsupply.com	(407) 298-7100
Digi-Key	www.digikey.com	(800) 338-1003
EBV Elektronik	www.ebv.com/en/locations.html	(49) 8121 774-0
Farnell InOne	www.farnellinone.com	+44 8701 200 200
Future Electronics Europe	www.futureelectronics.com/contact	info-eur-future@futureelectronics.com
Future & FAI Electronics	www.futureelectronics.com/contact	1-800-FUTURE1 (388-8731)
Marubun/Arrow	www.marubunarrow.com	(852) 2375-1126
Minco	www.mincotech.com	(512) 834-2022
Mouser Electronics	www.mouser.com	(800) 346-6873
Newark Electronics	www.newark.com	(800) 4-NEWARK
NU Horizons	www.nuhorizons.com	(888) 747-6846
NuVision	www.nuvision-tech.com	(886) 2 8228-0688
Rochester Electronics	www.rocelec.com	(978) 462-9332
Semi Dice Inc	www.semidice.com	1 (800) 345-6633
Silica (An Avnet Company)	www.silica.com	+33 1 6447 2929
WPI	www.wpi-group.com	(886) 2 2788-5200
Spoerle (An Arrow Company)	www.spoerle.de/de/about/offices	+49 6103 3040

INTERNATIONAL

BRAZIL	San Paulo	(55-11) 3842-8911
GREATER CHINA	Beijing	86-10-8518-2323
	Chengdu	86-28-8678-4078
	Hong Kong	852-2689-0088
	Shenzhen	86-755-8209-1128
	Shanghai	86-21-5131-7168
	Taipei, Taiwan	886-2-2377-9911

INTERNATIONAL

FRANCE	Paris	33 (0) 1 39-26-41-00
GERMANY	Munich	49 (0) 89-93-0808-0
INDIA	Bangalore	91-80-2532-5084
ISRAEL	Herzeliya	972 (0) 9-9609-111
ITALY	Milan	39 02 9239311
JAPAN	Tokyo	81-3-5773-3850
KOREA	Seoul	82-2-2190-3500

INTERNATIONAL

MALAYSIA	Penang	60-4-226-9368
MEXICO	Guadalajara	(5233) 3123-9199
SINGAPORE	Singapore	65-6391-1260
SLOVAKIA	Piestany	421 33 790 2450
UNITED KINGDOM	Slough	44 (0) 1753 70 1676

Feb-08

ON Semiconductor and the ON logo are registered trademarks of Semiconductor Components Industries, LLC (SCILLC). SCILLC reserves the right to make changes without further notice to any products herein. SCILLC makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does SCILLC assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in SCILLC data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. SCILLC does not convey any license under its patent rights nor the rights of others. SCILLC products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the SCILLC product could create a situation where personal injury or death may occur. Should Buyer purchase or use SCILLC products for any such unintended or unauthorized application, Buyer shall indemnify and hold SCILLC and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that SCILLC was negligent regarding the design or manufacture of the part. SCILLC is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor
P.O. Box 5163, Denver, Colorado 80217 USA
Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada
Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada
Email: orderlit@onsemi.com

N. American Technical Support: 800-282-9855 Toll Free
USA/Canada.

Europe, Middle East and Africa Technical Support:
Phone: 421 33 790 2910

Japan Customer Focus Center
Phone: 81-3-5773-3850

ON Semiconductor Website: www.onsemi.com

Order Literature: <http://www.onsemi.com/orderlit>

For additional information, please contact your local
Sales Representative