


Transformer, 1:3 5 MHz - 1200MHz

Rev. V1

Features

- ♦ 1:3 impedance ratio
- ♦ Surface mount
- Available on tape and reel
- ♦ 260°C reflow compatible
- ◆ RoHS Compliant and Pb free
- Excellent temperature stability
- \bullet Can be used on 50Ω and 75Ω systems




Electrical Specifications: $Z_0 = 75\Omega$, $T_A = 25$ °C, $P_{in} = 0$ dBm

Parameter	Conditions	Units	Min	Тур	Max
Frequency Range		MHz	5		1200
Impedance		Ω		75	
Impedance Ratio				1:3	
Insertion Loss1 Pin1 to Pin2	5 - 50 MHz 50 - 1000 MHz 1000 - 1200 MHz	dB dB dB	- - -	0.75 1.10 1.75	1.20 1.90 2.25
Insertion Loss2 Pin1 to Pin3	5 - 50 MHz 50 - 1000 MHz 1000 - 1200 MHz	dB dB dB	- - -	0.70 1.10 1.90	1.30 2.20 2.50
Amplitude Unbalance	5 - 50 MHz 50 - 1000 MHz 1000 - 1200 MHz	dB dB dB	- - -	0.02 0.05 0.15	± 0.70 ± 0.70 ± 0.80
Phase Balance	5 - 50 MHz 50 - 1200 MHz	dB dB	-	0.6 6.6	±5.0 ±10.0
Input Return Loss	5 - 50 MHz 50 - 1000 MHz 1000 - 1200 MHz	dB dB dB	19 15 15	21 21 24	- - -

Pin Configuration

Pin No.	Function	
1	Input (PRI dot)	
2	Output 1 (SEC dot)	
3	Output 2 (SEC)	
4	Ground (PRI)	

Schematic



ADVANCED: Data Sheets contain information regarding a product M/A-COM Technology Solutions is considering for development. Performance is based on target specifications, simulated results, and/or prototype measurements. Commitment to develop is not guaranteed.

PRELIMINARY: Data Sheets contain information regarding a product M/A-COM Technology

North America Tel: 800.366.2266
 India Tel: +91.80.43537383
 China Tel: +86.21.2407.1588
 Visit www.macomtech.com for additional data sheets and product information.

Solutions has under development. Performance is based on engineering test. Spricifications are typical. Mechanical outline has been fixed. Letding find, samples and/or test datain any be available (APCION Technology Solutions In c. and its affiliates reserve the right to make Commitment to produce in volume is not burnanteed.





Transformer, 1:3 5 MHz - 1200MHz

Rev. V1

Insertion Loss: Pin1—Pin2









Amplitude Balance

Phase Balance







Return Loss: Input

typical. Mechanical outline has been fixed. Engined Commitment to produce in volume is not puranted

Return Loss: Output








Transformer, 1:3 5 MHz - 1200MHz


Rev. V1

Outline Drawing




- Dimensions in mm.
- 2. Tolerance: ±0.2mm unless otherwise noted.
- 3. Model number and lot code are printed on the reel.
- Finish: ENIG

Recommended DC bias circuit



Cap/Ind	5-50MHz	50-1200MHz	
С	100nF	10nF	
L	10μH	1µH	

Recommended Footprint



• India Tel: +91.80.43537383

• North America Tel: 800.366.2266 • Europe Tel: +353.21.244.6400

• China Tel: +86.21.2407.1588



Transformer, 1:3 5 MHz - 1200MHz

Rev. V1

Tape & Reel Information

Parameter	Units	Value
Qty per reel	-	900
Reel size	mm	330
Tape width	mm	16.00
Pitch	mm	12.00
A ₀	mm	6.70
B ₀	mm	7.50
K ₀	mm	3.60
Orientation	-	F27

Ordering Information

Part Number	Description
MABA -010441-CT38A0	Tape & Reel
MABA -010441-CT38TB	Customer Evaluation Board

Recommended Maximum Ratings

Parameter	Units	Min	Max
Input Power	mW		250
DC Current	mA		200
Operating Temperature Range	°C	-40	+85
Storage Temperature Range	°C	-55	+125

Temperature data available on request

ECO History

Rev	Date	Description	ECN No.	
V1	20 August 2010	Created datasheet	20101164	

North America Tel: 800.366.2266
 India Tel: +91.80.43537383
 China Tel: +86.21.2407.1588
 Visit www.macomtech.com for additional data sheets and product information.