

## **RFXF0573**

### 1:16 SMT TRANSFORMER

Package: S-20






#### **Features**

- Frequency Range 5MHz to 40MHz
- Low Cost and RoHS Compliant
- Flux Coupled
- Industry Standard SMT package
- Available in Tape-and -Reel
- $50\Omega$  Characteristic Impedance

### **Applications**

- Broadband/CATV
- Wireless



Schematic

### **Product Description**

The RFXF0573 Transformer is designed for applications that require small, low cost, and highly reliable surface mount components. Applications may be found in broadband, wireless and other communications systems. These units are built Lead-Free and RoHS compliant. S-Parameters are available on request.

### **Ordering Information**

Part Number	Description	Reel Siz	e Package
RFXF0573SB	5 MHz to 40 MHz 1:16 SMT Transformer	N/A	5-piece bag
RFXF0573SQ	5 MHz to 40 MHz 1:16 SMT Transformer	N/A	25-piece bag
RFXF0573SR	5 MHz to 40 MHz 1:16 SMT Transformer	13"	100-piece reel
RFXF0573TR13	5 MHz to 40 MHz 1:16 SMT Transformer	13" 1	LOOO-piece reel

### **Optimum Technology Matching® Applied**

☐ GaAs HBT	☐ SiGe BiCMOS	☐ GaAs pHEMT	☐ GaN HEMT
☐ GaAs MESFET	☐ Si BiCMOS	☐ Si CMOS	☐ BiFET HBT
☐ InGaP HBT	☐ SiGe HBT	☐ Si BJT	☐ LDMOS

# **RFXF0573**



### **Absolute Maximum Ratings**

Parameter	Rating	Unit
RF Power	2	W
Operating Temperature	-45 to +85	°C
Storage Temperature	-55 to +100	°C



Exceeding any one or a combination of the Absolute Maximum Rating conditions may cause permanent damage to the device. Extended application of Absolute Maximum Rating conditions to the device may reduce device reliability. Specified typical performance or functional operation of the device under Absolute Maximum Rating conditions is not implied.


RoHS status based on EUDirective 2002/95/EC (at time of this document revision).

The information in this publication is believed to be accurate and reliable. However, no responsibility is assumed by RF Micro Devices, Inc. ("RFMD") for its use, nor for any infringement of patents, or other rights of third parties, resulting from its use. No license is granted by implication or otherwise under any patent or patent rights of RFMD. RFMD reserves the right to change component circuitry, recommended application circuitry and specifications at any time without prior notice.


Parameter	Sı	pecificati	on	Unit	Condition	
Farameter	Min.	Тур.	Max.		Condition	
					Typical values represent Mid-Band performance at 25 °C	
Frequency Range	5		40	MHz		
Insertion Loss <1 dB	5		40	MHz		
Insertion Loss <2 dB	-		-	MHz		
Insertion Loss <3 dB	-		-	MHz		
Amplitude Balance		0.1	0.3	dB		
Phase Balance		1.0	3.0	۰		
Impedance Ratio	1:16					
Type - Flux Coupled	Unbalanced to Balanced		d			




## **Performance Plots**













### Pin Out

Pin	Function
1	Secondary
2	Secondary CT
3	Secondary Dot
4	Primary Dot
5	Primary

## Package Drawing - S20

Dimensions in inches (millimeters)





## PCB FOOTPRINT

