

Item	Num	Lvl	Rev	WJ	Part Number	Description	MFR Part Number	CAGE Code	Qty	Per	Ref	Mfr Name
0	1	-			452632-000	REF. ASSY. APP BOARD. HIGH-POWER AMPLIFIER					.0000	
0	1	--1			452960-000	REF. FP31QF APP BOARD. FINAL TEST REQUIREMENTS					.0000	
1	1	--4			452354-001	FAB. HEAT SINK					1.0000	
2	1	-			860000-608	SCREW. MCH. SKTHD. ALN. 2-56. 0.188. SS	070206CHSCAZZ				6.0000	FASTENER SERVICE
3	1	-			034031-000	WASHER. SPLIT. #2. MEDIUM. SS	MS35338-134	96906			6.0000	MILITARY STD
4	1	-			850000-703	WASHER. FLAT. #2. SMALL. SS	25089X0149X016XCAZZ	NONE			6.0000	FASTENER SERVICE
6	1	-B			412724-018	CAP. 2.2PF. +/-0.05PF. 50V. ACCU-P. SMD. 0603	06035J2R2AAWTR 06035J2R2ABTTR				1.0000 C2	AVX AVX
7	1	-B			412724-017	CAP. 2PF. +/-0.05PF. 50V. ACCU-P. SMD. 0603	06031J2R0ABTTR 06035J2R0AAWTR 06035J2R0ABTTR	04222 04222			1.0000 C3	AVX AVX AVX
8	1	-A			412720-017	CAP. 22PF. 5PCT. 50V. NPO/COG. SMD. 0603	06035A220JAT1A 500R14N220JV4E ECUY1H220JCV GMC10CG220J50NT GRM39COG220J050AL LC-CC410603CG220J5NT	04222 29454 0J4G8			4.0000 C1 C10 C4 C8	AVX JOHANSON DIELECTRICS PANASONIC CAL-CHIP MURATA LAUBE
9	1	-			861000-459	RES. 5.1. 5PCT. 1/16W. CHIP. SMD. 0603	ERJ-3GSYJ5R1V RM06J5R1CT				1.0000 R1	PANASONIC CAL-CHIP
10	1	-			862000-567	IND. 12NH. 5PCT. CER CORE. SMD. 0805. SRF 4000MHZ	0805CS-120XJBC				2.0000 L1 L2	COILCRAFT
11	1	-			860000-523	IND. 4.7NH. +/-0.3NH. MULTILAYER. SMD. 0603. 4800MHZ	CTLL1608-4N7S LL1608-FH4N7S				1.0000 L3	CENTRAL TECHNOLOGIES TOKO
12	1	-A			412720-037	CAP. 1000PF. 5PCT. 50V. X7R. SMD. 0603	06035C102JAT1A 500R14W102JV4E ECUY1H102JBV GMC10X7R102J50NT GRM39X7R102J050AL	04222 29454 0J4G8			2.0000 C11 C7	AVX JOHANSON DIELECTRICS PANASONIC CAL-CHIP MURATA
13	1	-			850000-200	CAP. 0.1UF. 10PCT. 50V. X7R. SMD. 1206	12065C104KAT1A 500R18W104KV4E ECJ-3VB1H104K ECU-Y1H104KBW GMC31X7R104K50NTM GRM426X7R104K050AL				1.0000 C12	AVX JOHANSON DIELECTRICS PANASONIC PANASONIC CAL-CHIP MURATA
14	1	-B			412721-093	RES. 51.0. 5PCT. 1/16W. CHIP. SMD. 0603	CRCW0603510JRT2 ERJ3GSYJ510H LR-HPWAJ0510T50 RM73B1JTE510J	0J4G8 59124			1.0000 R2	DALE PANASONIC LAUBE KOA
15	1	--1			FP31QF-F ** SUB ** FP31QF	HFET. 2WATT. GAAS. DC-3GHZ. 6X6MM QFN HFET. 2WATT. GAAS. DC-3GHZ. 6X6MM QFN					1.0000 Q1	
16	1	-			445930-001	REF. NO LOAD PART					12.0000 C1 C2 C3 C4 C5	

Item Num	Lvl	Rev	WJ Part Number	Description	MFR Part Number	CAGE Code	Qty Per	Ref Desg	Mfr Name
								C6	
								C8	
								L1	
								L2	
								L3	
								R1	
17	1	-	862000-422	CONN. RF. SMA. F. STRT. FLANGE MOUNT. 1	142-0701-851		2.0000	J1 J2	JOHNSON COMPONENTS
18	1	-	862000-138	CONN. DC. HDR. STRT. TH. 1	2101-3-00-01-00-00-07-0		3.0000	J3 J4 J5	MIL-MAX
19	1	-	452924PC	PCB. APP BOARD, FP31QF. 24 BOARDS/PANEL			.0417		

Report successfully completed